

DF-G1 - Expert Fiber Amplifier Install Sheet



more sensors, more solutions

Advanced sensor with dual digital displays for use with plastic and glass fiber optic assemblies

For complete technical information about this product, including dimensions, accessories, and specifications, see www.bannerengineering.com and search 161999.

Overview




Figure 1. DF-G1 Model Features

1	Output LED
2	LO/DO Switch
3	RUN/PRG/ADJ Mode Switch
4	Lever Action Fiber Clamp
5	Red Signal Level
6	Green Threshold
7	+ /SET/ - Rocker Button



WARNING: Not To Be Used for Personnel Protection

Never use this device as a sensing device for personnel protection. Doing so could lead to serious injury or death. This device does not include the self-checking redundant circuitry necessary to allow its use in personnel safety applications. A sensor failure or malfunction can cause either an energized or de-energized sensor output condition.

Models

Model	Outputs	Connector ¹
DF-G1-NS-2M	Single NPN	2 m (6.5 ft) cable, 4-wire
DF-G1-PS-2M	Single PNP	
DF-G1-KS-2M	Dual outputs, 1 push-pull IO-Link and 1 PNP (complementary outputs)	
DF-G1-NS-Q5	Single NPN	150 mm (6 in) PVC pigtail, M12 Euro QD connector, 4-pin
DF-G1-PS-Q5	Single PNP	
DF-G1-KS-Q5	Dual outputs, 1 push-pull IO-Link and 1 PNP (complementary outputs)	
DF-G1-NS-Q7	Single NPN	Integral M8 Pico QD connector, 4-pin
DF-G1-PS-Q7	Single PNP	
DF-G1-KS-Q7	Dual outputs, 1 push-pull IO-Link and 1 PNP (complementary outputs)	


¹ Connector options:

- A model with a QD connector requires a mating cordset.
- For 9 m cable, change the suffix 2M to **9M** in the 2 m model number (example, DF-G1-NS-**9M**).
- For 150 mm (6 in) PVC pigtail, M8 Pico QD connector, 4-pin change the suffix 2M to **Q3** in the 2 m model number (example, DF-G1-NS-**Q3**).




Hookups


NPN Models



PNP Models




IO-Link Models




Key

- 1 = Brown
- 2 = White
- 3 = Blue
- 4 = Black

Euro



Pico




For cable options, see <http://www.bannerengineering.com>

Mounting Instructions


Mount on a DIN Rail

1. Hook the DIN rail clip on the bottom of the DF-G1 over the edge of the DIN rail (1).
2. Push the DF-G1 up on the DIN rail (1).
3. Pivot the DF-G1 onto the DIN rail, pressing until it snaps into place (2).




Mount to the Accessory Bracket

1. Position the DF-G1 in the SA-DIN-BRACKET.
2. Insert the supplied M3 screws.
3. Tighten the screws.



Remove from a DIN rail


1. Push the DF-G1 up on the DIN rail (1).
2. Pivot the DF-G1 away from the DIN rail and remove it (2).



Installing the Fibers

Follow these steps to install glass or plastic fibers.

1. Open the dust cover.
2. Move the fiber clamp forward to unlock it.
3. Insert the fibers into the fiber ports until they stop.
4. Move the fiber clamp backward to lock the fibers.
5. Close the dust cover.



Top Panel Interface

Opening the dust cover provides access to the top panel interface. The top panel interface consists of the RUN/PRG/ADJ mode switch, LO/DO switch, +/-SET/- rocker button, dual red/green digital displays, and output LED.

RUN/PRG/ADJ Mode Switch




The RUN/PRG/ADJ mode switch puts the sensor in RUN, PRG (Program), or ADJ (Adjust) mode. RUN mode allows the sensor to operate normally and prevents unintentional programming changes via the +/-SET/- button. PRG mode allows the sensor to be programmed through the display driven programming menu (see **Program Mode** below). ADJ mode allows the user to perform Expert TEACH/SET methods and Manual Adjust (see **Adjust Mode** below).

LO/DO Switch



The LO/DO switch is used to select Light Operate or Dark Operate mode. In Light Operate mode, the output is ON when the sensing condition is above the threshold (for Window SET, the output is ON when the sensing condition is inside the window). In Dark Operate mode, the output is ON when the sensing condition is below the threshold (for Window SET, the output is ON when the sensing condition is outside the window).

+/-SET/- Rocker Button



The +/-SET/- rocker button is a 3-way button. The +/- positions are engaged by rocking the button left/right. The SET position is engaged by clicking down the button while the rocker is in the middle position. All three button positions are used during PRG mode to navigate the display driven programming menu. During ADJ mode, SET is used to perform TEACH/SET methods and +/- are used to manually adjust the threshold(s). The rocker button is disabled during RUN mode, except when using Window SET, see [Window SET](#) on page 7.

Red/Green Digital Displays



During RUN and ADJ mode, the Red display shows the signal level and the Green display shows the threshold. During PRG mode, both displays are used to navigate the display driven programming menu.




Output LED

The output LED provides a visible indication when the output is activated.

Remote Input/IO-Link

For more information about how to perform TEACH/SET methods, to program the sensor remotely, or to interface with the sensor via IO-Link, see the DF-G1 Manual (P/N 161999).



Run Mode

Run mode allows the sensor to operate normally and prevents unintentional programming changes. The +/-SET/- rocker button is disabled during RUN mode, except when using Window SET, see [Window SET](#) on page 7.


RUN PRG ADJ

Program Mode

Program (PRG) mode allows the following settings to be programmed in the DF-G1 :

Factory Default Settings:

Setting	Factory Default
Threshold	2026
TEACH Selection	Two-Point TEACH
Response Speed	Standard - 500 μs
Offset Percent	10%
Auto Thresholds	OFF
OFF Delay	0 (Disabled)
OFF One-Shot	0 (Disabled)
ON Delay	0 (Disabled)
ON One-Shot	0 (Disabled)
Display Readout	Numeric, ECO disabled, Normal Orientation
Gain Selection	Auto Gain





Adjust Mode

Sliding the RUN/PRG/ADJ mode switch to the ADJ position allows the user to perform Expert TEACH/SET methods and Manual Adjustment of the threshold(s).

Two-Point TEACH

- Establishes a single switching threshold
- Threshold can be adjusted using "+" and "-" rocker button (Manual Adjust)

Two-Point TEACH is used when two conditions can be presented statically to the sensor. The sensor locates a single sensing threshold (the switchpoint) midway between the two taught conditions, with the Output ON condition on one side, and the Output OFF condition on the other (see Figure below). The Output ON and OFF conditions can be reversed by using the LO/DO (Light Operate/ Dark Operate) switch (see **LO/DO Switch** in *Top Panel Interface* on page 3).




Figure 2. Two-Point TEACH (Light Operate shown)

Two-Point TEACH and Manual Adjust Moves switching threshold value up or down to make adjustments

- Slide Mode switch to ADJ to enter Adjust mode
- Press "+" to increase; press "-" to decrease
 - GREEN display shows the switching threshold value
 - 2 seconds after adjustment, the GREEN display will flash 3 times to confirm
- Slide Mode switch to RUN to complete operation



Remember: Manual adjustments are disabled when Auto Thresholds are ON

	SET Button 0.04 seconds < "Click" < 0.8 seconds	Remote Input 0.04 seconds < T < 0.8 seconds	Result
<p>Note: TEACH Selection must be programmed to 2Pt tch (see <i>Program Mode</i> on page 4)</p>			
Enter Adjust Mode	Set Mode switch to ADJ 	No action required; sensor is ready for Two-Point TEACH method	Display: Red - Signal Level; Green - Threshold
TEACH 1st Condition	<ul style="list-style-type: none"> • Present 1st condition • Click the SET rocker button 	<ul style="list-style-type: none"> • Present 1st condition • Single-pulse remote input 	Display: Flashes "2Pt tch" then holds on "1234 2nd"
TEACH 2nd Condition	<ul style="list-style-type: none"> • Present 2nd condition • Click the SET rocker button 	<ul style="list-style-type: none"> • Present 2nd condition • Single-pulse remote input 	TEACH Accepted Displays alternate "PASS" and % Minimum Difference*; Sensor returns to Adjust mode
			TEACH Unacceptable Displays alternate "FAIL" and % Minimum Difference*; Sensor returns to Adjust mode
Return to RUN Mode	Move Mode switch to RUN 	No action required; sensor returns to RUN mode automatically	Display: Red - Signal Level; Green - Threshold

*See *Troubleshooting* on page 11 for more explanation of the % Minimum Difference displayed after the Two-Point TEACH method.

Dynamic TEACH

- Teaches on-the-fly
- Establishes a single switching threshold
- Threshold can be adjusted using "+" and "-" rocker button (Manual Adjust)

Dynamic TEACH is best used when a machine or process may not be stopped for teaching. The sensor learns during actual sensing conditions, taking multiple samples of the light and dark conditions and automatically setting the threshold at the optimum level (see Figure below).

The output ON and OFF conditions can be reversed using the LO/DO switch (see **LO/DO Switch** in [Top Panel Interface](#) on page 3).

Dynamic TEACH and Manual Adjust

Moves switching threshold value up or down to make adjustments

- Slide Mode switch to ADJ to enter Adjust mode
- Press "+" to increase; press "-" to decrease
 - GREEN display shows the switching threshold value
 - 2 seconds after adjustment, GREEN display will flash 3 times to confirm
- Slide Mode switch to RUN to complete operation



Remember: Manual adjustments are disabled when Auto Thresholds are ON




Figure 3. Dynamic TEACH (Light Operate shown)

	SET Button 0.04 seconds ≤ "Click" < 0.8 seconds	Remote Input 0.04 seconds ≤ T < 0.8 seconds	Result
<p>Note: TEACH Selection must be programmed to dYn tch (see Program Mode on page 4)</p>			
Enter Adjust Mode 	<ul style="list-style-type: none"> • Set Mode switch to ADJ 	No action required; sensor is ready for Dynamic TEACH method	Display: Red - Signal Level; Green - Threshold
Enter Dynamic TEACH 	<ul style="list-style-type: none"> • Click the SET rocker button 	<ul style="list-style-type: none"> • Single-pulse remote input 	Display: Flashes "dYn tch" then holds on "1234 dYn"
Present ON and OFF Conditions	<ul style="list-style-type: none"> • Present ON and OFF conditions 	<ul style="list-style-type: none"> • Present ON and OFF conditions 	Display: Red - Signal Level; Green - Threshold
Exit Dynamic TEACH 	<ul style="list-style-type: none"> • Click the SET rocker button 	<ul style="list-style-type: none"> • Single-pulse remote input 	TEACH Accepted Displays alternate "PASS" with % Minimum Difference*, Sensor returns to Adjust mode
			TEACH Unacceptable Displays alternate "FAIL" with % Minimum Difference*, Sensor returns to Adjust mode
Return to RUN Mode 	<ul style="list-style-type: none"> • Move Mode switch to RUN 	No action required; sensor returns to RUN mode automatically	Display: Red - Signal Level; Green - Threshold

*See [Troubleshooting](#) on page 11 for more explanation of the % Minimum Difference displayed after the Dynamic TEACH method.

Window SET

- Sets window thresholds that extend a programmable % offset above and below the presented condition
- All other conditions (lighter or darker) cause the output to change state
- Sensing window center can be adjusted using "+" and "-" rocker button (Manual Adjust)
- Recommended for applications where a product may not always appear in the same place, or when other signals may appear
- See Program Mode in the user's manual for programming the Offset Percent setting (to increase/decrease the window size)

A single sensing condition is presented, and the sensor positions window thresholds a programmable % offset above and below the presented condition. In LO mode, Window SET designates a sensing window with the Output ON condition inside the window, and the Output OFF conditions outside the window (see Figure below).

Output ON and OFF conditions can be reversed using the LO/DO switch (see **LO/DO Switch** in *Top Panel Interface* on page 3).




Figure 4. Window SET (Light Operate shown)

Window SET and Manual Adjust

Moves sensing window center value up or down to make adjustments

- Slide Mode switch to ADJ to enter Adjust mode
- Press "+" to increase; press "-" to decrease
 - GREEN display shows the sensing window center value
 - 2 seconds after adjustment, the GREEN display will flash 3 times to confirm
- Slide Mode switch to RUN to complete operation



Remember: Manual adjustments are disabled when Auto Thresholds are ON

	SET Button 0.04 seconds < "Click" < 0.8 seconds	Remote Input 0.04 seconds < T < 0.8 seconds	Result
<div style="background-color: #e0e0e0; padding: 10px; display: inline-block;"> <p>Note: TEACH Selection must be programmed to wind SET (see Program Mode on page 4)</p> </div>			
Enter Adjust Mode 	<ul style="list-style-type: none"> • Set Mode switch to ADJ 	No action required; sensor is ready for Window SET method	Display: Red - Signal Level; Green - Threshold
SET Sensing Condition 	<ul style="list-style-type: none"> • Present sensing condition • Click the SET rocker button 	<ul style="list-style-type: none"> • Present sensing condition • Single-pulse the remote input 	Threshold Condition Accepted Displays read "wind SET" then alternate "PASS" with % Offset*; Sensor returns to Adjust mode Threshold Condition Unacceptable Displays read "wind SET" then alternate "FAIL" with minimum % Offset* for sensing condition; Sensor returns to Adjust mode
Return to RUN Mode 	<ul style="list-style-type: none"> • Move Mode switch to RUN 	No action required; sensor returns to RUN mode automatically	Display: Red - Signal Level; Green - Window Center (see Figure below for instructions on how to display upper and lower thresholds) <div style="border: 1px solid black; padding: 5px; margin-top: 10px;"> <p>Window SET (during RUN mode) <small>Upon sensor power-up, Window Center is displayed</small></p> </div>

* See [Troubleshooting](#) on page 11 for more explanation of the % Offset displayed after the Window SET method

Light SET

- Sets a threshold a programmable % offset below the presented condition
- Changes output state on any condition darker than the threshold condition
- Threshold can be adjusted using "+" and "-" rocker button (Manual Adjust)
- Recommended for applications where only one condition is known, for example a stable light background with varying darker targets
- See [Program Mode](#) on page 4 for programming the Offset Percent setting

A single sensing condition is presented, and the sensor positions a threshold a programmable % offset below the presented condition. When a condition darker than the threshold is sensed, the output either turns ON or OFF, depending on the LO/DO switch setting (see [LO/DO Switch](#) in [Top Panel Interface](#) on page 3).

Light SET and Manual Adjust

Moves switching threshold value up or down to make adjustments

- Slide Mode switch to ADJ to enter Adjust mode
- Press "+" to increase; press "-" to decrease
 - GREEN display shows the switching threshold value
 - 2 seconds after adjustment, the GREEN display will flash 3 times to confirm
- Slide Mode switch to RUN to complete operation




Figure 5. Light SET (Light Operate shown)



Remember: Manual adjustments are disabled when Auto Thresholds are ON

	SET Button 0.04 seconds < "Click" < 0.8 seconds	Remote Input 0.04 seconds < T < 0.8 seconds	Result
<p>Note: TEACH Selection must be programmed to Lt SET (see Program Mode on page 4)</p>			
Enter Adjust Mode 	<ul style="list-style-type: none"> • Set Mode switch to ADJ 	No action is required; sensor is ready for Light SET method	Display: Red - Signal Level; Green - Threshold
SET Sensing Condition 	<ul style="list-style-type: none"> • Present sensing condition • Click the SET rocker button 	<ul style="list-style-type: none"> • Present sensing condition • Single-pulse the remote input 	Threshold Condition Accepted Displays read "Lt SET" then alternate "PASS" with % Offset*; Sensor returns to Adjust mode Threshold Condition Unacceptable Displays read "Lt SET" then alternate FAIL with minimum % Offset* for sensing condition; Sensor returns to Adjust mode
Return to RUN Mode 	<ul style="list-style-type: none"> • Move Mode switch to RUN 	No action required; sensor returns to RUN mode automatically	Display: Red - Signal Level; Green - Threshold

* See [Troubleshooting](#) on page 11 for more explanation of the % Offset displayed after the Light SET method


Dark SET

- Sets a threshold a programmable % offset above the presented condition
- Any condition lighter than the threshold condition causes the output to change state
- Threshold can be adjusted using "+" and "-" rocker button (Manual Adjust)
- Recommended for applications where only one condition is known, for example a stable dark background with varying lighter targets
- See [Program Mode](#) on page 4 for programming the Offset Percent setting



NOTE: Offset Percent MUST be programmed to **Minimum Offset** to accept conditions of no signal (0 counts).

A single sensing condition is presented, and the sensor positions a threshold a programmable % offset above the presented condition. When a condition lighter than the threshold is sensed, the output either turns ON or OFF, depending on the LO/DO switch setting (see [LO/DO Switch](#) in [Top Panel Interface](#) on page 3).



Dark SET and Manual Adjust

Moves switching threshold value up or down to make adjustments

- Slide Mode switch to ADJ to enter Adjust mode
- Press "+" to increase; press "-" to decrease
 - GREEN display shows the switching threshold value
 - 2 seconds after adjustment, the GREEN display will flash 3 times to confirm
- Slide Mode switch to RUN to complete operation



Remember: Manual adjustments are disabled when Auto Thresholds are ON

Figure 6. Dark SET (Light Operate shown)

	SET Button 0.04 seconds < "Click" < 0.8 seconds	Remote Input 0.04 seconds < T < 0.8 seconds	Result
<p>Note: TEACH Selection must be programmed to dr SET (see Program Mode on page 4)</p>			
Enter Adjust Mode 	<ul style="list-style-type: none"> • Set Mode switch to ADJ 	No action required; sensor is ready for Dark SET method	Display: Red - Signal Level; Green - Threshold
SET Sensing Condition 	<ul style="list-style-type: none"> • Present sensing condition • Click the SET rocker button 	<ul style="list-style-type: none"> • Present sensing condition • Single-pulse the remote input 	Threshold Condition Accepted Displays read "dr SET" then alternate "PASS" with % Offset*; Sensor returns to Adjust mode Threshold Condition Unacceptable Displays read "dr SET" then alternate "FAIL" with minimum % Offset* for sensing condition; Sensor returns to Adjust mode
Return to RUN Mode 	<ul style="list-style-type: none"> • Move Mode switch to RUN 	No action required; sensor returns to RUN mode automatically	Display: Red - Signal Level; Green - Threshold

* See [Troubleshooting](#) on page 11 for more explanation of the % Offset displayed after the Dark SET method

Calibration SET

- Sets a threshold exactly at the presented condition
- Threshold can be adjusted using "+" and "-" rocker button (Manual Adjust)

A single sensing condition is presented, and the sensor positions a threshold exactly at the presented condition. When a condition lighter than the threshold is sensed, the output either turns ON or OFF, depending on the LO/DO switch setting (see **LO/DO Switch** in *Top Panel Interface* on page 3).

Calibration SET and Manual Adjust

Moves switching threshold value up or down to make adjustments

- Slide Mode switch to ADJ to enter Adjust mode
- Press "+" to increase; press "-" to decrease
 - GREEN display shows the switching threshold value
 - 2 seconds after adjustment, the GREEN display will flash 3 times to confirm
- Slide Mode switch to RUN to complete operation




Figure 7. Calibration SET (Light Operate shown)



Remember: Auto Thresholding is automatically disabled in Calibration SET

	SET Button 0.04 seconds < "Click" < 0.8 seconds	Remote Input 0.04 seconds < T < 0.8 seconds	Result
<p>Note: TEACH Selection must be programmed to CAL SET (see <i>Program Mode</i> on page 4)</p>			
Enter Adjust Mode 	<ul style="list-style-type: none"> • Set Mode switch to ADJ 	No action required; sensor is ready for Calibration SET method	Display: Red - Signal Level; Green - Threshold
SET Sensing Condition 	<ul style="list-style-type: none"> • Present sensing condition • Click the SET rocker button 	<ul style="list-style-type: none"> • Present sensing condition • Single-pulse the remote input 	Threshold Condition Accepted Displays read "cAL SET" then flashes "PASS"; Sensor returns to Adjust mode Threshold Condition Unacceptable Displays read "cAL SET" then flashes "FAIL"; Sensor returns to Adjust mode
Return to RUN Mode 	<ul style="list-style-type: none"> • Move Mode switch to RUN 	No action required; sensor returns to RUN mode automatically	Display: Red - Signal Level; Green - Threshold

Troubleshooting

Manual Adjustments Disabled

Manual adjustments are disabled when Auto Thresholds are ON. If a manual adjustment is attempted while Auto Thresholds are ON, the Green display will flash



% Minimum Difference after TEACH

The Two-Point and Dynamic TEACH methods will flash a % minimum difference on the displays after a PASS or FAIL.

Value	PASS/FAIL	Description
0-99%	FAIL	The difference of the taught conditions does not meet the required minimum
100-300%	PASS	The difference of the taught conditions just meets/exceeds the required minimum, minor sensing variables may affect sensing reliability
300-600%	PASS	The difference of the taught conditions sufficiently exceeds the required minimum, minor sensing variables will not affect sensing reliability
600% +	PASS	The difference of the taught conditions greatly exceeds the required minimum, very stable operation




% Offset after SET

The Window, Dark, and Light SET methods will flash a % offset on the displays after a PASS or FAIL.

SET Result	% Offset Meaning
PASS (with % Offset)	Displays the % offset used for the SET method
FAIL (with % Offset)	Displays the minimum required % offset necessary to PASS the SET method
FAIL (without % Offset)	Presented condition cannot be used for the SET method

Threshold Alert or Threshold Error

Severe contamination/changes in the taught condition can prevent the Auto Thresholds algorithm from optimizing the threshold(s).

State	Display	Description	Corrective Action
Threshold Alert	Alternates  and 	The threshold(s) cannot be optimized, but the sensor's output will still continue to function	Cleaning/correcting the sensing environment and/or a re-teach of the sensor is highly recommended
Threshold Error		The threshold(s) cannot be optimized, and the sensor's output will stop functioning	Cleaning/correcting the sensing environment and/or a re-teach of the sensor is required

Specifications

Sensing Beam

660 nm visible red

Supply Voltage

NPN/PNP models: 10 to 30V dc Class 2 (10% max ripple)

IO-Link models: 18 to 30V dc (10% max ripple)

Power and Current Consumption (exclusive of load)

Standard display mode: 960 mW, Current consumption < 40 mA at 24V dc

ECO display mode: 720 mW, Current consumption < 30 mA at 24V dc

Supply Protection Circuitry

Protected against reverse polarity, overvoltage, and transient voltages

Delay at Power Up

500 milliseconds max.; outputs do not conduct during this time

Output Configuration

NPN/PNP models: 1 current sinking (NPN) or 1 current sourcing (PNP) output, depending on model

IO-Link models: 1 push-pull and 1 PNP (complementary outputs)

Output Rating

100 mA max. load (derate 1 mA per °C above 30 °C)

OFF-state leakage current: **NPN/PNP models:** < 5 µA at 30V dc; **IO-Link models:** < 50 µA at 30V dc

ON-state saturation voltage: **NPN:** < 1.5V; **PNP /IO-Link:** < 2V

Output Protection

Protected against output short-circuit, continuous overload, transient over-voltages, and false pulse on power up

Output Response Time

High Speed: 200 µs; Standard: 500 µs; Long Range: 2 ms; Extra Long Range: 5 ms

Repeatability

High Speed: 66 µs, Standard/Long Range/Extra Long Range: 100 µs

Construction

Black ABS/polycarbonate alloy (UL94 V-0 rated) housing, clear polycarbonate cover

Environmental Rating

IEC IP50, NEMA 1

Operating Conditions

Temperature: -10 °C to +55 °C (+14 °F to +131 °F)

Storage Temperature: -20 °C to +85 °C (-4 °F to +185 °F)

Humidity: 90% at +60 °C maximum relative humidity (non-condensing)

IO-Link Interface

Supports Smart Sensor Profile: Yes

Baud Rate: 38,400 bps (COM2)

Process Data Width: 16 bits

IODD files: Provide all programming options of top panel interface, plus additional functionality, see the DF-G1 Manual (P/N 161999)

Certifications



Banner Engineering Corp Limited Warranty

Banner Engineering Corp. warrants its products to be free from defects in material and workmanship for one year following the date of shipment. Banner Engineering Corp. will repair or replace, free of charge, any product of its manufacture which, at the time it is returned to the factory, is found to have been defective during the warranty period. This warranty does not cover damage or liability for misuse, abuse, or the improper application or installation of the Banner product.

THIS LIMITED WARRANTY IS EXCLUSIVE AND IN LIEU OF ALL OTHER WARRANTIES WHETHER EXPRESS OR IMPLIED (INCLUDING, WITHOUT LIMITATION, ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE), AND WHETHER ARISING UNDER COURSE OF PERFORMANCE, COURSE OF DEALING OR TRADE USAGE.

This Warranty is exclusive and limited to repair or, at the discretion of Banner Engineering Corp., replacement. **IN NO EVENT SHALL BANNER ENGINEERING CORP. BE LIABLE TO BUYER OR ANY OTHER PERSON OR ENTITY FOR ANY EXTRA COSTS, EXPENSES, LOSSES, LOSS OF PROFITS, OR ANY INCIDENTAL, CONSEQUENTIAL OR SPECIAL DAMAGES RESULTING FROM ANY PRODUCT DEFECT OR FROM THE USE OR INABILITY TO USE THE PRODUCT, WHETHER ARISING IN CONTRACT OR WARRANTY, STATUTE, TORT, STRICT LIABILITY, NEGLIGENCE, OR OTHERWISE.**

Banner Engineering Corp. reserves the right to change, modify or improve the design of the product without assuming any obligations or liabilities relating to any product previously manufactured by Banner Engineering Corp.



more sensors, more solutions