



0.25" c. bore x 0.3" dp, 0.16" dia. 0.64cm c. bore x 0.76cm dp, 0.64cm dia. 0.20" 0.51cm 2.00" 5.08 cm 0.38" 0.25" 0.03" 0.64cm 0.8cm 0.38" 0.97cm (\bigcirc) (0)1 60' 4.06cm Magnet Part No. 1081

(included)

Screw Mount With Wire Leads

1085 Series

Applications

- · Convenient surface mounting
- · Mounting screws included

General Specifications

Enclosure **ABS Plastic** Temperature Range -40°F to 150°F (-40°C to 65°C) Environmental Hermetically Sealed Reed Switch Encapsulated in Polyurethane **NEMA Rating** 1, 2, 3, 4, 4x, 5, 6, 12 IP 67 **Protection Class** Response Time 1 msec max. Life Cycles 100,000 Under Full Load, 10,000,000 Under Dry Circuit Lead Types/O.D. #22 wire / 0.05" (0.15cm) Color Choices Natural(N), Mahogany(M), Grey(G) **UL/ULC Listed** All Models

Order Information		Electrical Specifications		;			
Part Number	Contact ¹ Configuration	Load Rating (AC/DC)	Switching Voltage (AC/DC)	Switching Current (AC/DC)	Contact Resistance	Sense Range ² Nominal	Lead Length
1085-G, M, N	N.O.	7.5W/VA	100V	0.5A	0.2 Ohms	0.6" (1.6cm)	1'
1085W-M, N	N.O.	7.5W/VA	100V	0.5A	0.2 Ohms	1.5" (3.8cm)	1'
1086-N	N.C.	3W/VA	30V	0.25A	0.2 Ohms	0.6" (1.6cm)	1'
1086W-M	N.C.	3W/VA	30V	0.25A	0.2 Ohms	1.5" (3.8cm)	1'
1081-N	Actuator Only						

Warning— Each electrical rating is an individual maximum and cannot be exceeded!

- Configuration with actuator away from the switch
- Proximity of ferrous materials usually reduces sense range typically by 50%. The shape and type of material cause a wide diversity of effects. Testing is required to determine actual sense range for specific applications. As measured on a nonferrous surface.
 Gap distances are nominal make distance ± 20%. Gap Specifications are for switch to make. Break distance is approximately 1.1 to 1.5 times make.

76 1-800-336-4206 www.edwardssignaling.com